



DPA-770 is a PA amplifier with an inbuilt MP3 Digital Player, making it a versatile multi-application music center. The Digital Player accepts USB drives, and reproduces clear, high quality music. A remote control is provided for controlling the functions of the Digital Player from a distance. This, combined with 4 microphone inputs, 1 Aux input, and provision for multiple speaker connections makes this ideally suitable for a variety of music programmes and public address applications.

- 4 Mic & 1 Aux Input.
- Built-in MP3 player with USB reader and remote control.
- Line Output for connecting to a Booster Amplifier.
- Active Bass & Treble controls.
- Instant transfer to DC Power (Car Battery) if AC power fails.
- 5 LED array for output level monitoring.

Specifications

POWER OUTPUT	100W Max., 75W RMS at 10% THD, 70W RMS at 5% THD
INPUT CHANNELS	4 × Mic. 0.6mV/4.7kΩ, 1 × Aux 100mV/330kΩ
FREQUENCY RESPONSE	50-15,000Hz ±3dB
SIGNAL TO NOISE RATIO	55dB
TONE CONTROLS	Bass: -10dB, +7dB at 100Hz Treble: -10dB, +7dB at 10kHz
OUTPUTS	Line: 1V/3.5kΩ
SPEAKER OUTPUTS	4Ω, 8Ω, 16Ω & 100V
DIGITAL PLAYER	MP3 Player with USB reader
POWER SUPPLY	AC: 220-240V 50/60Hz, DC: 12-14V Car Battery
DIMENSIONS	W385 × H130 × D310 mm
WEIGHT	9.4kg